

## CDMA Rejection Filter

### Product Description

Band Pass Filters are used to pass the required frequency band and to reject unwanted frequencies. This filter is designed to suppress the CDMA Signals to avoid interference in GSM Network.


### Technical Specifications

<b>Model No</b>	<b>303 306 08</b>
Frequency (MHz)	890 – 960
Insertion Loss @ 890 – 894 MHz (dB)	4.5 (Max)
Insertion Loss @ 894 – 900 MHz (dB)	1.5 (Max)
Return Loss (dB)	18 (Typ) 14 (Min)
Attenuation @ 889 MHz(dB)	10
Attenuation @ 860 - 888 MHz (dB)	30 (Min)
Impedance (Ohms)	50
Average Power(dBm)	50 CW
Connector	DIN 7/16 Female

### Mechanical Specifications

Dimension (LxWxH) (mm)	180x94x39
Weight(grams)	1500
Material	Aluminium Alloy
Finish	Spray Painted
Temperature Range	-20°C to +70°C

### Filter characteristics



### Product Photo

